

# Remote access controller with built-in wireless receiver

**PR-6750V** 



## **Product Description**

PR-6750V is a remote access controller with built-in wireless receiver. It can be used with electric lock as access control system or with relay box and Key transmitter (Four keys) as car parking system. Optional transmitter (PTM series) with embedded RFID chip can be applied to both parking and access control system. The transmitter capacity: 1,000~32,000pcs

#### **Features**

- With hopping code anti-copied remote access controller, transmitter capacity: 1,000~32,000 pcs. (Depending on the model)
- With *up* .stop .down and power outage relay, combination relay box with key transmitter (Four keys) as car parking system.
- If using duplicated transmitter without hopping code supported, the door will not be opened.
- You can add/delete the transmitter authorization upon your request by manual control or on-line with PC, and recording entrance/out time.

### **Specification**

Dimensions(L x W x H)mm : 137 x 85 x 29 : 340g ± 5% Net weight

: DC 12V±10%, 80mA(Standby) / 100mA(Working) Power supply

Reading range : 15 m Frequency of operation : 433.9MHz Operating temperature : 0oC ~ 70oC Operating humidity : 10%~90%





## **Key transmitter series**



## **Ordering information**

#### Access control system:

PR-6750V Remote access controllerPTX-201 Key transmitter (Signal key)Electric lock Electric strike / Electric dropbolt /

Electromagnetic locks

#### Car parking system:

PR-6750V Remote access controller
PTX-204 Key transmitter(Four key)
PG-OUTMOD-4 Relay box(For 4 relays output)

## PONGEE INDUSTRIES CO., LTD.

5F., No.738, Chung-Cheng Rd., Chung-Ho District, New Taipei City 235603, Taiwan

Tel: 886-2-82280198 Fax: 886-2-82280191

E-mail: pongee@pongee.com.tw Website:http://www.pongee.com
We reserve the right to change the specification without prior notice or obligation!

